





RF COAXIAL TERMINATIONS




SMA-50JR		
	Characteristic Impedance	50 Ω
	Frequency range	0~18GHz
	VSWR	≤1.25
	Power capacity	1 W

SMA-50KR		
	Characteristic Impedance	50 Ω
	Frequency range	0~18GHz
	VSWR	≤1.25
	Power capacity	1 W


SMA-50JR2		
	Characteristic Impedance	50 Ω
	Frequency range	0~12GHz
	VSWR	≤1.30
	Power capacity	2 W

SMA-50JR5		
	Characteristic Impedance	50 Ω
	Frequency range	0~8GHz
	VSWR	≤1.30
	Power capacity	5 W


N-50JR

	Characteristic Impedance	50 Ω
	Frequency range	0~18GHz
	VSWR	≤1.25
	Power capacity	1 W


N-50JR5

	Characteristic Impedance	50 Ω
	Frequency range	0~8GHz
	VSWR	≤1.30
	Power capacity	5 W


BNC-50JR

	Characteristic Impedance	50 Ω
	Frequency range	0~3GHz
	VSWR	≤1.25
	Power capacity	2 W


BNC-50KR

	Characteristic Impedance	50 Ω
	Frequency range	0~3GHz
	VSWR	≤1.25
	Power capacity	2 W


BNC-75JR

	Characteristic Impedance	75 Ω
	Frequency range	0~1GHz
	VSWR	≤1.25
	Power capacity	2 W


BNC-75KR

	Characteristic Impedance	75 Ω
	Frequency range	0~1GHz
	VSWR	≤1.25
	Power capacity	2 W


TNC-50JR

	Characteristic Impedance	50 Ω
	Frequency range	0~12GHz
	VSWR	≤1.25
	Power capacity	1 W


TNC-50KR

	Characteristic Impedance	50 Ω
	Frequency range	0~12GHz
	VSWR	≤1.25
	Power capacity	1 W

TNC-50JR2

	Characteristic Impedance	50 Ω
	Frequency range	0~12GHz
	VSWR	≤1.25
	Power capacity	2 W

TNC-50KR2

	Characteristic Impedance	50 Ω
	Frequency range	0~12GHz
	VSWR	≤1.25
	Power capacity	2 W